

**SONY®**

**SNC-P1 software upgrade manual**  
(ver1.01 to ver1.03)

Version 1.0

Oct / 29 / 2004

SONY Corporation

## 1. General description

This documentation explains the way to upgrade software of SONY Network Camera SNC-P1 (from ver1.01 to ver1.03).


## 2. Attention

We take no responsibility to any damage by the use of this at all. Moreover, this information may be changed without any announcement for the reason of upgrading the product and so on.

## 3. Confirmation of the current software version

Before starting to upgrade the software of the SNC-P1, confirmation of the current software version is recommended. Make sure that the software version of the SNC-P1 is shown as "1.01". The version confirmation can be made by the following procedure.

- # Open the "Advanced mode" menu
- # Click the "System" icon on the left side of the Advanced menu to emerge the "System" tab of the System setting menu
- # Make sure that the current software version is 1.01




#### 4. Upgrading software to 1.03beta (sncp1\_ver103beta.bin)

The upgrade procedure of the SNC-P1 software version 1.01 to 1.03 consists of 2 steps. The first one is to upgrade the software to 1.03beta by using a file named "sncp1\_ver103beta.bin". The next one is to upgrade the software to 1.03 by using a file named "sncp1\_ver103.bin".


# Click the Initialize icon to emerge the Initialize tab

# Click "browse" button to select the "sncp1\_ver103beta.bin" file to upload to the camera.

**NOTE :** Do not select a file other than an upgrade file for SNC-P1.



Click "OK" in the emerged dialog box to start uploading the file and upgrading



Click "OK"

After you click "OK" button, the uploading process will be started, followed by the upgrading process.


**NOTE:** While the uploading process is in progress (you will see the progress indicator in the status bar in the browser window), DO NOT close the setting window.

When the uploading process is finished, the SNC-P1 will start the upgrading process. During the upgrading process, the blue LED on the top of the SNC-P1 will be blinking. **DO NOT** turn off the camera during this period. This upgrading process will take approximately 4 or 5 minutes to be finished. The camera will restart its reboot process automatically after the software upgrade.

## 5. Confirmation of the software upgrade (1.03beta)

See to it if the software upgrade will be successfully finished by the following procedure.

- # Open the Advance mode Menu
- # Click the "System" icon on the left side of the Advanced menu to emerge the "System" tab of the System setting menu
- # Make sure that the software version is shown 1.03beta



## 6. Upgrading software to 1.03 (sncp1\_ver103.bin)

Go on to the next software upgrading process of "1.03beta" to "1.03". Use the "sncp1\_ver103.bin" file to upgrade and follow the same procedure shown in the section 4 and 5.

**NOTE:** While the uploading process is in progress (you will see the progress indicator in the status bar in the browser window), DO NOT close the setting window.

When the uploading process is finished, the SNC-P1 will start the upgrading process. During the upgrading process, the blue LED on the top of the SNC-P1 will be blinking. DO NOT turn off the camera during this period.

The upgrading process will take approximately 4 or 5 minutes to be finished and the camera will start its reboot process automatically. Follow the same procedure shown in the section 5 to make sure that the software version is upgraded to "1.03".

## Version history

Version	Date	Comment
1.0	2004. 10. 29	First issue