



DVI-D端子(DVI-D、凹)




| | | | |
|----|-----------------------|----|--------------------------|
| 1 | T.M.D.S. Data2- | 14 | +5 V Power |
| 2 | T.M.D.S. Data2+ | 15 | Ground (return for +5 V) |
| 3 | T.M.D.S. Data2 Shield | | |
| 4 | NC | 16 | Hot Plug Detect |
| 5 | NC | 17 | T.M.D.S. Data0- |
| 6 | DDC Clock | 18 | T.M.D.S. Data0+ |
| 7 | DDC Data | 19 | T.M.D.S. Data0 Shield |
| 8 | NC | 20 | NC |
| 9 | T.M.D.S. Data1- | 21 | NC |
| 10 | T.M.D.S. Data1+ | 22 | T.M.D.S. Clock Shield |
| 11 | T.M.D.S. Data1 Shield | 23 | T.M.D.S. Clock+ |
| 12 | NC | 24 | T.M.D.S. Clock- |
| 13 | NC | | |

RGB入力端子(ミニ D-sub15ピン、凹)




| | | | |
|---|------------|----|----------|
| 1 | 映像入力 (赤) R | 9 | DDC用電源入力 |
| 2 | 映像入力 (緑) G | 10 | 接地 |
| 3 | 映像入力 (青) B | 11 | 接地 |
| 4 | 接地 | 12 | DDC/SDA |
| 5 | RESERVE | 13 | 水平同期信号 |
| 6 | 接地 (赤用) | 14 | 垂直同期信号 |
| 7 | 接地 (緑用) | 15 | DDC/SCL |
| 8 | 接地 (青用) | | |

RS-232C端子(D-Sub 9ピン、凸)



| | | | |
|---|------|---|-----|
| 1 | NC | 6 | NC |
| 2 | RXDA | 7 | RTS |
| 3 | TXDA | 8 | CTS |
| 4 | DTR | 9 | NC |
| 5 | GND | | |

HDMI端子(HDMI、凹)



| | | | |
|----|--------------------------|----|--------------------------|
| 1 | T.M.D.S. Data2+ | 11 | T.M.D.S. Clock Shield |
| 2 | T.M.D.S. Data2 Shield | 12 | T.M.D.S. Clock - |
| 3 | T.M.D.S. Data2 - | 13 | NC |
| 4 | T.M.D.S. Data1 + | 14 | RESERVED (N.C.) |
| 5 | T.M.D.S. Data1 Shield | 15 | SCL |
| 6 | T.M.D.S. Data1 - | 16 | SDA |
| 7 | T.M.D.S. Data0+ | 17 | GND |
| 8 | T.M.D.S. Data0 Shield | 18 | +5V Power |
| 9 | T.M.D.S. Data0 - | 19 | Hot Plug Detect |
| 10 | T.M.D.S. Clock+ | | |